



## Sound Levels from Kongsberg Multibeam's and Single beams

|           |   |
|-----------|---|
| Doc ID:   | 454146  |
| Revision: | D   |
| Status:   | This document is under configuration control at Kongsberg Maritime. |

## Document history

| Revision | Description of Change  |
|----------|--|
| A        | First Issue  |
| B        | Systems EM1002 and EM200 are removed, Systems EM2040 and EM2040C are added |
| C        | Revised with source level for Single beams in a separate table             |
| D        | Added calc. for reduced Power (PL) affecting Source Level for MB/SB        |
|          |  |
|          |  |

## References

| No | Doc No       | Description           |
|----|--------------|-----------------------|
| 1  | KM-TMPL-0000 | KM Main Word Template |
| 2  |              |                       |
| 3  |              |                       |
|    |              |                       |

## Disclaimer

Kongsberg Maritime AS endeavours to ensure that all information in this document is correct and fairly stated, but does not accept liability for any errors or omissions unless and to the extent otherwise is expressly agreed in writing between the parties under contract.

## Table of contents

|   |                            |   |
|---|----------------------------|---|
| 1 | Theory of calculation..... | 5 |
| 2 | Multibeam Systems.....     | 6 |
| 3 | Single Beams .....         | 8 |

## Table of figures

|           |                        |   |
|-----------|------------------------|---|
| Figure 1. | Multibeam systems..... | 7 |
| Figure 2. | Single beam.....       | 8 |

## Definitions / Abbreviations

|    |                    |
|----|--------------------|
| MB | Multi beam         |
| SB | Single Beam        |
| SL | Source Level       |
| TP | Transmit Power     |
| BW | Band Width         |
| TR | Transmit response  |
| RS | Receive Response   |
| PL | Power Level        |
| NF | Nearfield Distance |

## 1 THEORY OF CALCULATION

The power output level of an echo sounder is normally specified by giving its source level in dB relative to 1  $\mu\text{Pa}$  at a distance of 1 m from the transmit transducer. However, this is really a measure of the pressure level of the output sound wave and is only directly applicable in the farfield. The intensity (power per unit area) of a sound wave can be found from the pressure level by the relation  $I = p^2/\rho c$  where  $\rho$  is the water density and  $c$  the speed of sound. The quantity  $\rho c$  is the acoustic impedance of water and for sea water is nominally taken to be  $1.5 \times 10^6 \text{ kg/m}^2\text{s}$ . Thus, a pressure level in sea water of 1  $\mu\text{Pa}$  is nominally equal to an energy intensity of  $0.667 \times 10^{-18} \text{ W/m}^2$ , and a pressure level of for example 210 dB corresponds to an intensity of  $667 \text{ W/m}^2$ .

In the farfield the pressure level of a sound wave will fall off with the square of the distance, this because of spherical spreading of the wave, and the wave will be further attenuated due to absorption loss. In the nearfield the pressure level will be nominally constant as there is no spreading. If the transmit transducer generating the sound wave is rectangular, there will be a transition region in which the pressure will fall off proportionally to the distance due to cylindrical spreading in the direction parallel to the shortest side of the transducer. It may be noted that in the nearfield the pressure level will have large variations, with peaks up to about twice the nominal level and also deep nulls, this effect will however be ignored in this note.

The source level is given by  $SL = 170.8 + 10 \lg P_{Ac} + DI$ .  $P_{Ac}$  is the acoustic power which is typically half the electric power applied to the transmit transducer.  $DI$  is the transducer's directivity index which for a rectangular flat transducer can be approximated by  $DI = 46.2 - 10 \lg \theta_x \theta_y$  where  $\theta_x$  and  $\theta_y$  are the transmit beam widths in degrees along and across respectively. The relation between beam width and transducer array length,  $L$ , depends upon the applied shading and the number of elements in the array, typically it would be  $\theta = 65\lambda/L$  where  $\lambda$  is the wavelength. The nearfield limit is conventionally given by  $R = L^2/\lambda$ .

To derive the pressure levels in the nearfield from the source level of an echo sounder one must first calculate the pressure level at the largest farfield limit assuming spherical spreading from the 1-meter reference level used in defining the source level. From the largest to the smallest nearfield limit the pressure level will increase linearly with distance, and from the smallest nearfield limit into the transducer level the pressure level will be constant.

If the source level of the echo sounder is not known, but both beam widths or transducer array lengths or even just area are, the maximum possible pressure level may still to a good degree be estimated. Then one must rely upon the fact that there is a maximum acoustic power intensity that can be applied to a transducer in the order of 2-5  $\text{W/cm}^2$  to avoid cavitation (lowest number is typical at say 12 kHz, highest at say 100 kHz). With shading being applied in one direction the power will be reduced to about 50-60%, and for both directions to about 30%.

The calculations outlined above are for the on-axis direction (usually straight down). Off-axis the pressure level will fall rapidly for a narrow beam (along track for a multibeam echo sounder), the level will be 20 dB down at a little more than twice the beam width. Across track, the pressure level will typically be 20 dB down for angles of more than 75-80° of the vertical for flat arrays. At for example 45° the closest nearfield distance will be half that of on-axis, leading to a

3-dB reduction in pressure level for distances larger than the nearfield distance on-axis. At 60° the nearfield distance will be reduced by another factor of two and considering the usual level reduction at large beam angles also, the pressure level would typically be down about 8 dB compared to on-axis. At 70° the level will be about 16 dB down due a further halving of the nearfield distance and the beam pattern drop-off. For multibeams which use sectorized transmission such as most current Kongsberg systems, beam defocusing is applied in the central sector(s) in shallow waters which implies that the nearfield will be shortened and the drop-off in pressure level starts earlier.

Sonars may be transmitting horizontally and with a sound speed profile where the sound speed lessens toward the surface the spreading will cylindrical even in the farfield due to ducting causing a sound channel at the surface. For multibeam echo sounders this is usually not the case, except for tilted systems such as with the dual head EM 3002.

The following table shows the relevant parameters for the currently available Kongsberg multibeam echo sounders. For each model the along track (transmit) beam width, the source level in dB re 1  $\mu$ Pa at 1 meter, calculated nearfield distances and pressure levels in dB re 1  $\mu$ Pa at the nearfield distances are provided. The effect of absorption loss is not included in this table.

## 2 MULTIBEAM SYSTEMS

| System                | SL  | NF1      | PL@NF1 | NF2    | PL@NF2 |
|-----------------------|-----|----------|--------|--------|--------|
| SBP 120/300/27/29 3°  | 230 | 0.8 m    | 209    | 138 m  | 187    |
| SBP 120/300/27/29 6°  | 224 | 0.8 m    | 209    | 34 m   | 193    |
| SBP 120/300/27/29 12° | 218 | 0.8 m    | 210    | 8 m    | 200    |
| EM 122/124 0.5°       | 245 | 3.5 m    | 207    | 1749 m | 180    |
| EM 120/122/124 1°     | 242 | 3.5 m    | 210    | 438 m  | 189    |
| EM 120/122/124 2°     | 236 | 3.5 m    | 210    | 110 m  | 195    |
| EM 302 /304 0.5°      | 241 | 1.3 m    | 211    | 704 m  | 184    |
| EM 300/302/304 1°     | 237 | 1.3 m    | 213    | 175 m  | 192    |
| EM 300/302/304 2°     | 231 | 1.3 m    | 213    | 43 m   | 198    |
| EM 710/712 0.5°       | 232 | 0.3 m    | 213    | 246 m  | 184    |
| EM 710/712 1°         | 228 | 0.3 m    | 215    | 61 m   | 192    |
| EM 710/712 2°         | 222 | 0.3 m    | 215    | 15 m   | 198    |
| EM 3002 (1.5°)        | 216 | 0.01 m   | 227    | 8 m    | 198    |
| EM 2040 (0.5°)        | 217 | 0.002 m  | 225    | 82 m   | 179    |
| EM 2040 (1.0°)        | 211 | 0.002 m  | 225    | 20 m   | 185    |
| EM 2040C (1.3°)       | 205 | 0.0005 m | 227    | 11 m   | 183    |

In the next table the pressure levels at a set of fixed distances are given and also the range at which the pressure level is 180 dB re 1  $\mu$ Pa. Note that the figures are worst case, i.e. on-axis and with no defocusing. Note also that in this table absorption loss has been taken into account, but not in the former, using absorption coefficients of 0.2 dB/km at 4 kHz, 1 dB/km at 12 kHz, 6 dB/km at 30 kHz, 30 dB/km at 100 kHz, 50 dB/km at 200 kHz and 70 dB/km at 300 kHz.

| System                | PL<br>@1m | PL<br>@10m | PL<br>@100m | PL<br>@1000m | R<br>@180dB |
|-----------------------|-----------|------------|-------------|--------------|-------------|
| SBP 120/300/27/29 3°  | 209       | 199        | 189         | 170          | 314 m       |
| SBP 120/300/27/29 6°  | 209       | 199        | 184         | 164          | 158 m       |
| SBP 120/300/27/29 12° | 209       | 198        | 178         | 158          | 79 m        |
| EM 122/124 0.5°       | 207       | 203        | 192         | 182          | 1331 m      |
| EM 120/122/124 1°     | 210       | 206        | 195         | 181          | 1108 m      |
| EM 120/122/124 2°     | 210       | 206        | 195         | 175          | 590 m       |
| EM 302/304 0.5°       | 211       | 202        | 192         | 175          | 690 m       |
| EM 300/302/304 1°     | 213       | 205        | 194         | 171          | 501 m       |
| EM 300/302/304 2°     | 213       | 205        | 190         | 165          | 290 m       |
| EM 710/712 0.5°       | 208       | 198        | 185         | 142          | 183 m       |
| EM 710/712 1°         | 210       | 200        | 185         | 138          | 150 m       |
| EM 710/712 2°         | 210       | 200        | 179         | 132          | 92 m        |
| EM 3002 (1.5°)        | 207       | 195        | 169         | 86           | 44 m        |
| EM 2040 (0.5°)        | 198       | 187        | 170         | 87           | 35 m        |
| EM 2040 (1.0°)        | 198       | 187        | 164         | 81           | 28 m        |
| EM 2040C (1.3°)       | 194       | 183        | 158         | 75           | 15 m        |

Figure 1. Multibeam systems

---

Note! *Source level (SL) are reduced with 3dB when the Transmit Power (PL) is reduced with 50%. Source Level (SL) are reduced with 6dB when the voltage is reduced with 50%*

---

### 3 SINGLE BEAMS

The table below shows the Source Level (SL) for all Single beam transducers.  
Some abbreviations for this list: (For combi transducers the lowest frequency is first)

SL: Source Level in dB (re 1 $\mu$ pa per 1m)

TP: Transmit Power (Max) (in Watts)

BW: Band Width (in degrees), If not circular Longitudinal first.

TR: Transmit Response in dB (re 1 $\mu$ pa per V)

RS: Receive Response in dB (re 1V per  $\mu$ pa)

| System                        | SL               | TP          | BW             | TR                                 | RS             |
|-------------------------------|------------------|-------------|----------------|------------------------------------|----------------|
| 12Khz 12-16/60 18+1 Element   | 221,8            | 2000        | 16             | 171                                | -168,5         |
| 12Khz 12-16/60 1 Wide Element | 197,8            | 100         | 60             | 142                                | -168,5         |
| 15Khz (15-17 Airmar)          | 228,4            | 4000        | 17             | 165                                | -175           |
| 18Khz (18/11)                 | 225,8            | 2000        | 11 $\pm$ 2     | 176 $\pm$ 2                        | -168 $\pm$ 2   |
| 38Khz (38/7)                  | 230,1            | 2000        | 7              | 182,5 $\pm$ 2                      | -170,5 $\pm$ 2 |
| 38Khz (38/9)                  | 225,6            | 1500        | 9              | 177                                | -171           |
| 38/200Khz (Combi W)           | 222,8<br>/220,7  | 400<br>/250 | 31             | 164 /155                           | -184 / -197    |
| 38/200Khz (Combi C and D)     | 218,8 /<br>226,3 | 1000        | 13/21 and<br>7 | 170 /178                           | -178 / -185    |
| 50Khz (50/7)                  | 228,8            | 2000        | 7              | 177,5                              | -173           |
| 50Khz (50/18)                 | 214,8            | 500         | 18 $\pm$ 3     | 207 $\pm$ 2                        | -181 $\pm$ 2   |
| 50/200 Khz (Combi C and D)    | 221 /<br>227     | 1000        | 10/16 and<br>7 | 172 / 178                          | -179 / -185    |
| 120Khz (120-25)               | 227,8            | 1000        | 10 $\pm$ 2     | 176,5 $\pm$ 2                      | -183 $\pm$ 2   |
| 120Khz (SideScan)             | 223,3            | 1000        | 1,9/55         | ?                                  | ?              |
| 200Khz (200 7F)               | 226,3            | 1000        | 7 $\pm$ 1      | 180 $\pm$ 2                        | -185 $\pm$ 2   |
| 200Khz (200 7G)               | 226,3            | 1000        | 7 $\pm$ 1      | 215 $\pm$ 2 re 1<br>$\mu$ pa per A | -185 $\pm$ 2   |
| 200Khz (200 9G)               | 221,6            | 500         | 9              | 175 $\pm$ 2                        | -169 $\pm$ 2   |
| 200Khz (200 28E)              | 228              | 1500        | 7 $\pm$ 1      | 180 $\pm$ 2                        | -185 $\pm$ 2   |
| 200Khz (200-35E)              | 235,8            | 2000        | 3 $\pm$ 0.5    | 186,5                              | -177           |
| 200Khz (Side Scan)            | 226,8            | 1000        | 0,5/49         | 182 $\pm$ 2                        | -167 $\pm$ 2   |
| 500Khz (500-3G)               | 231,4            | 500         | 3              | 186 $\pm$ 2                        | -189 $\pm$ 2   |
| 500Khz ( SideScan)            | 230,8            | 1000        | 0,35 / 60      | 179                                | -196           |

Figure 2. Single beam

---

**Note!** *Source level (SL) are reduced with 3dB when the Transmit Power (PL) is reduced with 50%. Source Level (SL) are reduced with 6dB when the voltage is reduced with 50%*

---